

#### AHD/CVI/TVI To Fiber Converters CHD0101-720

♦ 1 channel AHD/CVI/TVI with 1channel Reverse RS485 Data to fiber converter (720P)

#### Features

- Aluminum alloy shell, wall mount or 2U chassis
- Support 1280\*720P,1280\*960P for AHD/CVI,1280\*720P for TVI
- All interface adopt three grade anti-static, lightning protection
- Wide optical dynamic range and advanced adaptive technology, transmission distance can reach up to 60Km
- Surface mount devices ensure products high stability, high reliability
- Low electromagnetic interference (EMI) and radio frequency interference (RFI)
- Abundant LED indicators, diagnostic indication
- Plug and Play, hot plugged
- Small size, low power consumption, strong interference resistance
- Industry-grade of operating temperature from -40  $^{\circ}$ C to 75  $^{\circ}$ C, which is applied to the different working environment
- Support user customization and OEM
- Compatible with AHD/CVI/TVI Cameras



#### Introduction

CHD0101-720 can transmit 1 channel AHD/CVI/TVI over one multimode or single-mode optical fiber. Electronic and optical adjustments are never required. LED indicators are provided for instantly monitoring system status. Devices are available for either standalone or rack-mount installation, which is suitable for different working environment . Compatible with 1280\*720P,1280\*960P for AHD/CVI, 1280\*720P for TVI. Lossless non-compression real time transmission

### Application

- Intelligent Transportation System
- Connection of Sub-network for Surveillance Center
- Public Security Surveillance
- High Way & Toll Station Surveillance
- Industrial Closed Circuit Television Surveillance
- Military monitoring (warehouses, border guards, defense)









# > Specification

Optical	
Wavelength	1310nm&1550nm
Output Power	-8~3dBm
Optic fiber	50/125u multimode, 62.5/125u multimode, 9/125u single mode
ax sensitivity	-22dBm
ptical connector	FC,ST,SC (optional)
istance	0~500M (multi mode) / 20,40,60Km (Single mode)
ideo	
umber of Channels	1
put/output impedance	BNC 75Ω OHM(unbalance)
tandard video input/output oltage	1.0Vp-p
ideo Bandwidth	60MHz
ampling Bandwidth	8bit
ampling Frequency	120MHz
ise and Fall time	<0.8ns
Optical Signal Intrinsic Jitter	<0.2 UI
ifferential Gain	$<\pm1.5\%$
ifferential Phase	< ±1 °
onnector	BNC
ther	
ower	DC5V 2A
ower Consumption	5W
emperature	-40 ℃ ~75 ℃
umidity	10%~90% RH
nit Weight	0.5Kg(pair)
imension	110mm×87mm×30mm
nstallation	Wall mount or 2U 19" chassis
<b>ITBF</b>	Greater than or equal≥ 100000Hours

# Ordering Information

Model NO.	Description
CHD0101-720	1 channel AHD/CVI/TVI with 1channel Reverse RS485 Data to fiber converter
CHD0100-720	1 channel AHD/CVI/TVI to fiber converter

### **Dimension**



## > Connection diagram

